

Features

- Keyer speed range: 5 - 99 WPM
- Automatic touch sensitivity calibration
- Dynamically allocated message memory
- Keying Modes: Bug, Ultimatic, Iambic A or B
- Audio Frequency keying mode
- Adjustable Weighting: 25 to 75 %
- Adjustable Keying Compensation: 0 to 31 mSec
- Paddle swap command
- Continuously adjustable Sidetone frequency
- Speed control potentiometer
- Two User Configurations each with callsign
- Power Consumption: <1 ma
- HSCW and QRSS support
- Non-Volatile Message Memory: 240 letters in 12 Slots/dual banked with embedded commands.
- Integrated Touch Paddle Input
- 39 easy to use commands
- Supply Voltage Monitor
- Serial Number Generation
- Adjustable Letter Spacing: 25 to 75%
- Automatic letter space mode (Autospace)
- Beacon: Programmable interval: 1 to 99 seconds
- Sidetone Output: On board mini-speaker
- Key/PTT Output: Open collector up to 60VDC
- Push-button user interface
- Supply Voltage: 7-13.5 VDC (on board regulator)
- Backspace supported on message entry
- Rx and Tx Practice Modes
- Configure as keyer or paddle

Description

The PS1 is a dual function device that can act as a simple touch paddle or a full function iambic keyer with touch paddle input. Optimal touch paddle sensitivity is maintained by an autocalibration algorithm that runs continually. PS1 is implemented in a Microchip PIC16F1825 microcontroller and utilizes the K1EL K16 keyer core (K16-PS) which provides a wide range of features. A single jumper configures the device in paddle or keyer mode. In keyer mode, setup commands are directly entered on the paddles in Morse code. All settings and messages are stored in nonvolatile memory so that settings are preserved when the keyer is turned off and on. The K16 keyer core has many original features not found in other keyers:

• Supply Voltage Monitoring

The K16-PS has a unique feature that is useful in battery powered applications. It can accurately monitor its supply voltage and provide an indication when battery voltage is low. Normally the K16-PS will respond with an **R** when entering command mode. If the battery voltage is approaching the minimum operating limit, it will respond with an **L** instead. This tells the operator that the batteries need to be replaced. The actual supply voltage can be read out in Morse by using the **V** command in the extended command set. See page 23. Note that a voltage regulator maintains the keyer supply voltage at five volts until the power supply drops below approx. 6 volts.

• Dual User Configuration

The K16-PS provides storage for two complete configuration setups. For example, one setup could be used for contesting while the other for casual operating. Or, when two operators share the same keyer, each user can have their own setup profile. The extended command **U** is provided to select one configuration or the other. All K16-PS settings are included in each profile including a stored callsign. (page 23)

• Dual Message Banks

The K16-PS has two message banks of six slots plus two callsign slots. Total message storage is 240 bytes. While this does not seem like a lot of message space, due to the K16-PS's dynamic memory allocation scheme, it turns out to be more than adequate for most users. It is very easy to swap message banks with **E** command. This is the shortest command sequence and allows you to swap banks quickly. There is also a buffered message command **/E** that swaps message banks. (page 27)

• Stored Callsigns

A special memory slot is provided to store the operator's callsign. In fact there are two callsign slots provided, one for each user. The callsign is programmed by using a special callsign load command in the extended command set. The callsign can be embedded in a message with the **/M** buffered command. The callsign slot works like any other message slot, you can call other messages, embed commands, and there is no practical limit to the length of the string. (page 23)

• Wide range of embedded message commands

Please refer to the list on page 27.

- **Sidetone Frequency**

The K16-PS sidetone can be set to any frequency between 300 Hz and 2000Hz. (page 22)

- **Fast Message Interruption**

The K16-PS will stop a message immediately upon paddle press, stopping in mid-letter if need be.

- **Practice Mode**

Both send and receive practice are included. The user can select practice content by letter group so that easier letters can be mastered first followed by progressively more difficult groups. A very good random letter generator is provided which generates a varied, ever changing letter order. (page 20)

- **Message Stacking**

Up to 10 messages can be queued to be sent in the order requested.

- **Simplified Beacon Formatting**

For example, this is all that is required to setup a repeating 15 second beacon: **/B15 K1EL BCON**

- **Easy Beacon**

Any message slot can be turned into a beacon without having to add the special **/B** embedded command. The **B** command allows 'on the fly' beaoning without embedded commands. (page 18)

- **PTT Lead In and Tail Settings**

The K16-PS adopts the Winkeyer scheme for PTT control. Both the lead in delay and tail delay can be specified in milliseconds as well as speed dependent hang delay for paddle operation. (page 23)

- **Dit/Dah Ratio Control**

The timing of dits vs. dahs can be customized. A ratio of 1:3 is standard but this can be altered to suit different tastes. (page 22)

- **Improved Cut Number Selection**

The K16-PS allows serial number cuts to be used for 0, 9, both, or neither. (page 23)

- **Tuning Duty Cycle Selection**

Tune can be set to generate either a 50% or 100% key down duty cycle. (page 19)

- **Contest Word Spacing**

The K16-PS allows a shorter inter-word spacing to be selected. This is intended to speed up exchanges during contests. Standard word spacing is 7 dits while contest mode word spacing is 6 dits. (page 23)

- **Keyer Lock**

The K16-PS can be locked by command and it will stay locked until both paddles are pressed at the same time for eight seconds. While locked, the K16-PS will ignore any input and stays in a very low power sleep mode. This is useful for traveling or to prevent "accidental" keying while connected to a radio. (page 28)

- **Fixed Speed Setting**

The K16-PS supports both a variable speed control with a fixed "favorite" speed setting. It is very easy to switch between them. The fixed speed setting is set by the **S** command. (page 21)

- **Speed Pot Range Setting**

The upper and lower limit of the speed pot is set with a new extended command; **R** for range. Two values are entered the lowest speed pot setting followed by the highest speed pot setting. (page 23)

- **Paddle Serial Number Decrement**

A fast way to decrement the serial number is very useful during contests. The K16-PS allows this with a simultaneous command pushbutton and paddle press. (page 26)

- **First Element Extension**

This is another command that is brought over from the Winkeyer command set. It allows the first dit or dah of a transmission to be elongated to allow for receive to transmit relay delay. (page 23)

• Command Response Time Adjustment

The K16-PS will enter command mode when the command pushbutton is pressed for about 2 seconds. This may be too long for some operators. A new extended command **F** has been added that allows the delay to be shortened to about 1.3 seconds. (page 23)

• Full Time Speed Pot

The K16-PS responds to speed pot changes without delay, even while sending messages.

Paddle Stick Functional Block Diagram

Figure 1 is a block diagram of the PaddleStick (PS1) board. You can configure the operation of the PS1 with a single two pin jumper. When the jumper is in place, the PS1 will act as a simple touch paddle that can be attached to a radio that has a built in keyer. In other words, PS1 takes the place of an iambic paddle set. With the jumper out, PS1 operates as a standalone keyer that supports a speed control pot, four message pushbuttons, and a powerful, self-contained, Morse keyer. One of the push buttons is dual purpose, press and hold to enter commands or quick press to play a message. Also included on the PS1 board is a sidetone speaker and two open collector output buffers that provide either Key/PTT outputs or Left/Right paddle outputs. The paddle sensors are integrated into the PS1 circuit board which provide a very compact keyer/paddle set in one. The PS1 can be mounted in one of two ways. Two right angle brackets and hardware are included so that the PS1 can be mounted on the bottom or front.




Figure 1 – PaddleStick Block Diagram

Touch Paddle Configuration

Since the PS1 continually scans and adjusts paddle sensitivity based on current conditions, specific sensitivity adjustments are not required.

PaddleStick Kit Introduction

This kit consists of a printed circuit board, a K16-PS IC, sidetone speaker, keying output drivers, voltage regulator, speed pot interface, and a multiple pushbutton interface. The kit can be powered in one of two ways with or without the on board 5 volt regulator enabled. If the regulator is not used, it must be insured that the external power supply voltage does not exceed 5 volts.

PaddleStick Kit Assembly

Parts Inventory

U1	- K16-PS 14 pin DIP IC (16F1825)
VR1	- LM2936V TO92 5.0V regulator
Q1, Q2	- BS170 Transistor TO92
R1	- 56Ω 1/8 watt (green blue black)
R2	- 470Ω 1/8 watt (yellow violet brown)
R3, 4,	- 2.2KΩ 1% 1/8 watt (red red red)
R5, 6	- " " " "
C1	- .47 μF ceramic capacitor 474
C5	- .1 μF ceramic capacitor 104

C3	- .0047 uF blue 5% capacitor 472
C2, 4	- .001 uF ceramic capacitor 102
1 pc	- 14 Pin DIP Socket
1 pc	- PaddleStick R01 PC board
SP1	- Mini speaker
J2	- Two pin jumper set
HW1	- Two right angle 4-40 brackets
HW2	- Four 4-40 by 1/4" screw
HW3	- Two 4-40 plastic washers

Note: LM78L05 may be substituted for VR1

PCB Assembly




Figure 2 - PaddleStick PC Board before assembly

Use a pair of wire cutters to cut through the paddle separator holes, the perforations make it easy.:




Figure 3 – Cut paddle separator

Bend the paddle section to break it free. Trim off separator and use sandpaper to remove burs.




Figure 4 – Free paddle piece and then trim off separator.




Figure 5 – Install socket, pin 1 to upper left, and solder in place

On the main board, install the resistors first, R1 through R6. Color codes are listed in the bill of materials on page 4. We recommend verifying resistor values with an ohmmeter. These resistors are mounted standing up. See Figure 7 on the next page for illustration.

Install Capacitors: C1 through C5. C1 and C5 are the very small orange ceramic caps.




Figure 6 – Capacitor details, note that C1 is now .47uF (474)




Figure 7 – Installs Resistors and Capacitors

Install resistors and capacitors; use the bill of materials to identify resistors by color code. Note that the resistors are installed standing up. The capacitors are identified using Figure 6 on page 6.




Figure 8 – Install 2N7000 Transistors (Read Note Below!) and Voltage Regulator

IMPORTANT STEP: Early PS1 kits were shipped with 2N7000s for Q1 and Q2. Due to an error in the board's silkscreen, 2N7000s must be installed in reverse as shown in Figure 8. Current kit versions use BS170s for Q1 and Q2 which do not need to be reversed.




Figure 9 – Install Speaker and Jumper

Install and solder the mini speaker, plus pin into the square hole. Note that there are two sets of mounting holes to accommodate an alternate speaker type. You can remove and discard the protective white film cover. Install 2 pin jumper post J2, leave the jumper shunt off for now.

Install U1 (K16-PS)



Figure 10 – Trim foam panel to fit within paddle edges

If required, carefully trim the double sided foam piece so that it is about 1/16 of an inch smaller than the paddle. Slightly trim the end corners to match the paddle bevel. The panel needs to be short enough so that the solder via is accessible.




Figure 11 – Attach foam panel to free paddle, peel off backing.

Remove the adhesive backing and attach the pad to the free paddle. The pad goes on the surface that does **NOT** have the copper touch paddle pad (See Figure 10). Take your time with this step to make sure that the adhesive pad is aligned and centered (note red arrows). Insure that the solder pad is exposed (red circle).




Figure 12 – Join free paddle to main paddle board.

Remove the remaining adhesive backing and carefully line the paddles together as you press them together making one assembly.




Figure 11 – Detail view of free paddle in place.




Figure 12 – Completed assembly, power leads attached.

Solder a scrap resistor lead in place to electrically connect the free paddle to the main paddle board.




Figure 13 – Completed assembly, side view

Test Procedure

All external connections are made to the 12 pin array of pads marked J1 on the back edge of the PC board. The main signal groups are power/ground, pushbutton, dit/dah outputs.

Starting from the top, the connection points are:

- A** – Sidetone Audio
- G** – Ground
- P** – PTT or Dah paddle output
- K** – KEY or Dit paddle output
- C** – Command/MSG1 pushbutton
- 2** – Message 2 pushbutton
- 3** – Message 3 pushbutton
- 4** – Message 4 pushbutton
- S** – Speed Pot
- G** – Ground
- +** – Plus power supply
- G** – Ground

To start testing, first attach power leads. Be sure the positive lead goes to the pad marked **+** while the negative lead goes to the pad marked **G** for ground. For now wire a temporary jumper between pad **S** and **G**. The optimal supply voltage is 8 to 9 volts but higher voltages up to 13.5 volts will also work fine. Make sure that jumper J2 is NOT installed. After doubling checking power polarity, apply power and you should hear one “R” (di-dah-dit) in Morse from the speaker. Touch the paddle pads and you should hear dits and dahs.

Now the pushbutton array will be tested. Attach a short length of wire to power supply ground. Strip and tin the other end so that it can be used as a test lead. First, hold the ground lead on the **C** pad and after a few seconds you’ll hear an “R”. Release the test lead and after about 4 seconds the keyer will send a question mark (?). If you ground pads M2, M3, or M4 the keyer will respond by sending MT. This is shorthand for “eMpTy message slot”

If you don't get any of these tests to work carefully check the board for miswires or solder shorts. Refer to the images of the solder side and silkscreen to aid in your debugging.

Next we will look at ways of mounting the PS1 assembly and wiring up connectors and pushbuttons.

Now you can finish wiring up the paddle, keying, and push button connections. The K16 can be installed directly in your transceiver or in a separate enclosure.

How to connect your PaddleStick




Figure 14 - PaddleStick Connection Diagram

This is a diagram illustrating the various connections to the PS1. Note that there are various options available. Not all pushbuttons are required, PS1 will work fine with a single pushbutton tied to the command (C) input. Alternatively, 2, 3, or 4 message pushbuttons can be connected. The more pushbuttons, the more messages can be accessed. A speed pot is not a requirement, if you don't want to use one simply tie the S input to ground, this will tell the K16-PS to operate in fixed speed mode. The speed then is changed using the S command.

There are two sidetone audio output options. The first is an onboard piezo speaker or an external speaker.

The key and PTT outputs are open collector which means they act like a switch to ground. The key output can be directly connected to a transmitter key input. Beware that the Key output can only switch voltages up to 60V DC. It is not capable of directly keying a vacuum tube transmitter which employs negative keying voltages.

When configured for paddle mode (J2 installed) the Key and PTT outputs directly follow the touch paddles. The internal keyer is disabled and the PS1 can be used as a substitute for a set of iambic paddles.

Keyer Mounting

There are two mounting options; base mount or front panel mount. Two right angle brackets and hardware are included with the kit. In front panel mount, the paddle portion of the board would extend out of the front of an enclosure. A slot and two holes must be provided in the enclosure for this. In base mount, PS1 sits on a base and does not have to be in an enclosure. A weighted base works best since PS1 is very light and will move around if not weighted down. Since most base mount applications will require a power supply, batteries may provide enough weighting. Provisions can be made to mount the speed pot and pushbuttons.




Figure 15 – Base mount illustration




Figure 16 – Front panel mount illustration




Figure 17 – Picture of brackets installed

Keying Considerations

PS1 outputs are low true open collector using 2N7000 MOSFETs. These provide a very low on resistance so the PS1 will be able to key virtually any solid state transceiver. These outputs are capable of sinking 60 milliamps. The highest voltage that the PS1 can safely switch is 60 VDC so it would not be suitable for keying vacuum tube transmitters that utilize grid block or cathode keying. Solid state or reed relays are good solutions for keying these types of transmitters.

Input Considerations

Capacitive sensing pads are integrated into the PS1 printed circuit board. While these inputs have built in ESD protection, the safety margin can be increased by applying a layer of plastic tape to the paddles.

Command and Message Push-buttons

The PS1 requires at least one normally open push-button control, this switch is referred to as the command push-button and is connected to pad **C**. It serves two functions, command entry and message record/playback. Three additional message push-buttons can be added at pads **2**, **3** and **4** to provide a total of four direct access messages. Be sure to use normally open switches for the push-buttons. Two additional messages are accessed by pressing two pushbuttons in a specific sequence, see page 26 for more info.

Speed Pot

The speed pot is sensed by the same mechanism that reads pushbutton presses. The PS1 continuously monitors the speed pot position and pushbutton matrix state. The value of the speed pot must be 10K ohms, no other value may be substituted. If you choose not to use a speed pot, be sure to tie the S input to ground, to force the K16-PS to operate in fixed speed mode. When operating the K16-PS in this mode, speed changed can be done easily with the Fast WPM paddle feature.

PaddleStick Kit Schematics




Figure 18 – PaddleStick Schematic

PaddleStick PCB Images




Figure 19 – PaddleStick Silk Screen PCB Layer

Operating the PS1/K16-PS Keyer IC

The PS1 incorporates the K16 keyer core so it shares the same functionality as the K16. Presented here is the K16 documentation for reference.

Command Mode

Changes to the K16-PS's configuration are made by entering values on the paddles. Before doing this, the K16-PS must be put into command mode.

If the command push-button is pressed and held, the K16 will respond after about two seconds with the letter **R** in sidetone. This means the K16 is ready to accept a command. Simply enter the command letter in Morse on the paddles and the command will be executed. Some commands require additional parameters. In this case, the K16-PS will prompt you with the letter **E** (for enter). When the K16-PS is in command mode, the KEY and PTT outputs are inactive. All commands provide some sort of feedback to tell you if the command was understood and executed properly. If an illegal command or parameter is entered, the K16-PS will respond with a question mark.

Important Note ! When in command mode, transmitter keying is disabled and replies are sent in sidetone only. Thus in order to use command mode you must provide some way to hear the sidetone. If sidetone had been disabled with the **A** command it will be re-enabled automatically when entering command mode.

Command Toggles – Many settings such as Paddle Swap and Transmit Mute have just two states, on or off. These settings are turned on or off like a toggle switch. Issuing the command will change the state back and forth between off and on. When a toggle command is turned off, the K16-PS will echo an **N** for “Not enabled” Likewise when a toggle command is turned on an **A** is echoed for en**A**bled.

K16-PS Command List

A - Toggle sidetone on/off	N - Load 4 digit serial number
B - Easy Beacon	O - Swap keying output port
C - Set command speed in WPM	P - Start a Practice Session
D - Decrement serial number	Q - Query: Report current settings
E - Swap Message Banks	R - Review message without transmitting
F - Set Farnsworth Speed	S - Set Speed Pot Range
G - Toggle Tune Duty Cycle 50/100%	T - Set PTT Tail Delay
H - Set PTT Hang Delay	U - Toggle Autospadding on/off
I - Set Letter Spacing	V - Set Keying compensation in mSec
J - Set Paddle sensitivity	W - Set Key Weight
K - Select keyer mode	X - Enter Extended Command
L - Set PTT Lead In Delay	Y - Set Dit/Dah Ratio
M - Toggle Transmit Mute on/off	Z - Select sidetone frequency

In the command descriptions below, the **[n]** or **[nn]** notation means that additional parameters must be entered on the paddles after the command. A letter displayed in **BOLD** is something you enter, ***BOLD ITALIC*** is K16-PS response. **[pb]** means that the K16-PS will wait for you to press one of the message pushbuttons.

A - Sidetone enable: is toggled when this command is entered. Sidetone would be disabled when using a transceiver's built in sidetone generator. The K16-PS will acknowledge this command by responding with an **A**. Note: If sidetone is disabled, it will be temporarily re-enabled when entering comand mode.

B [m,dd] - Easy Beacon: Any message slot in the current bank can be repeated at a specified rate. After entering **B**, the user is prompted to enter a single digit message number (1-6) and then prompted to enter a two digit beacon cycle time (1-99) in seconds. A beacon is interrupted by hitting either paddle. The beacon is timed from start of beacon to start of next beacon. For example if you set a delay time of 10 seconds, the beacon will start every 10 seconds regardless how long the message is. If the message is longer than delay time, then there will be no gap between messages.

C [nn] – Command WPM: The K16-PS uses different speeds for command transactions and keyed transmit. Changes in transmit speed will not affect command speed. After the **C** command is issued enter the speed in

WPM. If the speed is valid the K16-PS responds with an **R**, otherwise a **?** See the **S** command for details on setting transmit Morse speed.

D - Decrement serial number by 1, K16-PS responds with a **D**

E - Swap message banks: The K16-PS has two separate message banks, six messages each. In response to this command, the K16-PS will respond with an **E** for bank one or an **I** for bank two.

F [nn] - Set Farnsworth Speed: This is used primarily for code practice. Letters are sent at the Farnsworth speed while maintaining the default code speed. For example, if Farnsworth is set to 25 WPM and the operating speed is set to 7 WPM, individual letters will be sent at 25 WPM while spacing between letters is at a 7 WPM rate. To disable Farnsworth mode, set it to zero.

G - Toggle 50% tune duty cycle: The default tune duty cycle is 100% key down. This command allows either 100% or 50% duty cycle to be selected. Some folks prefer a 50% tuning duty cycle to reduce power dissipation in transmitter finals and/or linear amplifier. An **A** is echoed when 50% is enabled, an **N** is echoed when set to 100%

H [n] - Set Transmit PTT Hang Delay Time: Sets a PTT delay that is proportional to sending speed. The delay begins after paddle sending stops. You can select one of four delays:

HangTime = 0: wait 1 wordspace + 1 dit before ending PTT
 HangTime = 1: wait 1 wordspace + 2 dits before ending PTT
 HangTime = 2: wait 1 wordspace + 4 dits before ending PTT
 HangTime = 3: wait 1 wordspace + 8 dits before ending PTT

After entering the command letter, you will be prompted with an **E** to enter the desired hang time as a number 0 to 3 as indicated in the table. Hang delay is different than PTT tail delay in that it is proportional to code speed while PTT delay is a primarily a fixed delay time. This means you don't have to change the PTT delay every time you change sending speed.

I [nn] - Set Letterspace Adjustment: nn is a value 0 to 31, specifying an additional letterspace to be applied between letters. Multiply nn by two to arrive at the actual adjustment percentage. For example a value of 7 applies 14% additional letterspace between letters. The maximum adjustment is 62%.

J [nn] - Paddle Sample Delay: normally the K16-PS waits one dit time after a paddle press has been sensed before latching a second paddle press. This command allows this delay time to be adjusted longer or shorter than one dit. If the delay is set too short, the keyer may send unwanted dits or dahs, if there is too much delay it can make sending a bit more tedious. From the formula provided below, delay time can be set to be greater or smaller than one dit time. The default value is 50 which specifies one dit time. Value of 99 doubles the delay time while a value of 25 halves the delay. Faster operators report a setting somewhat less than default has a nice feel. **If the paddle sensitivity is set to zero, both dit and dah paddle memories are disabled.** The delay is calculated with this formula:

$DELAY_TIME = (nn \times DIT_TIME) / 50$ where Switchpoint is a value between 01 and 99.

K - Set Keying Mode: There are six different keying modes supported by the K16-PS: Iambic mode A, Iambic mode B, Straight Key/Bug, Ultimatic, Dit priority mode, and Dah priority mode. In either Iambic mode, alternating dits and dahs are sent while both paddles are held closed. In mode B an extra alternate dit or dah is sent after both paddles are released. In straight key/bug mode a dah paddle press will key the transmitter for as long as the paddle is pressed and dits will be generated automatically when the dit paddle is pressed. In Ultimatic mode when both paddles are pressed the keyer will send a continuous stream of whichever paddle was last pressed. Hold dah then press dit->sends dits. Hold dit then press dah -> dahs are sent. Ultimatic dit and dah priority mode will generate dits and dahs automatically in response to single paddle presses, but when both paddles are pressed either dit or dah has priority.

After the **K** command is issued the current mode is set by entering a single letter:

Iambic B: Enter B
 Iambic A: Enter A
 Ultimatic: Enter U
 Straight Key: Enter S (This is also the Bug setting)
 Dit Priority: Enter E (Ultimatic with dits always taking priority when both pressed)
 Dah Priority: Enter T (Ultimatic with dahs always taking priority when both pressed)

L [nn] - **Set PTT Lead In Time** to a value between 0 and 99 milliseconds. See the Set PTT Lead/Tail description on page 23 for more information.

M - Toggle transmit mute: Mute transmit when you want to use the K16-PS as a Code Practice Oscillator (CPO) When muted, the K16-PS will send CW in sidetone only. In response to this command, the K16-PS will echo an **A** when mute is turned on and an **N** when mute is turned off.

N [nnnn] - **Load 4 Digit Serial Number:** All four digits must be entered including leading zeroes. The serial number is played by inserting a play message token **/N** into a message. The serial number is automatically incremented after playing. See *Embedded Command* section for more details.

O - Swap Key Output Port: Each time the **O** command is issued, the key port is toggled back and forth between key port 1 and key port 2. When port 1 is selected the K16-PS responds with a single dit and two dits are echoed when port 2 is selected. Note that port selection is only allowed when the PTT option is disabled. Normally Key port 2 is the K16-PS's PTT output. To disable PTT mode, use the extended command **P** which unlinks the PTT function and allows that port to be used as a second key output port. If you have two transceivers, this feature frees you from moving cables around when you want to switch radios.

P [m,d] - **Start Practice Mode:** A dual mode multi-level code practice program is built into the K16-PS. There are two styles of practice, receive only and echo (receive/respond) practice. There are four levels of practice organized by easy to difficult letter groups. The four levels are:

Level 1: E T A N I M W S G D U K O R
 Level 2: C Q P J F B V Y H X Z L including level 1
 Level 3: 1 2 3 4 5 6 7 8 9 0 including level 1 & 2
 Level 4: ? / , . A R S K B T A S including level 1 & 2 & 3

The syntax for entering a practice mode is:

P m d where m is R for receive or E for echo practice and d is a singel digit 1 to 4 to select diffculty level.

P R 2 selects Level 2 receive practice

P E 4 selects Level 4 echo practice

Receive Practice Description: Random characters from the selected level are sent in groups of five. Practice will continue until the command pushbutton is pressed.

Echo Receive/Transmit Practice Description: The K16-PS will send a random character from the selected level and you must respond by echoing the character back on the paddles. If you get it right the K16-PS will repeat the first character followed by a new character. Now you must echo back both characters. The K16-PS will continue to add characters until a set of five characters has been completed successfully. After that it will start over with a new set. If you miss a character the K16-PS will respond with an **X** and start over with a new sequence of characters.

When you want to end practice, either respond with di-dah-di-dah or press the command pushbutton. By default practice will be sent on the active output key port, enable transmit mute (**M** command) to inhibit this.

Q - Query K16-PS Current Settings: K16-PS will respond with current settings sent in the following format:

WPM is sent first
N followed by Serial Number
M followed by free msg memory space in letters available
C followed by command WPM
W followed by weight
L followed by lead time
T followed by tail time
E followed by 1st extension (this parameter described in host mode section)
V followed by key compensation
F followed by Farnsworth WPM
I followed by Letterspace adjustment
J followed by Paddle Sample Adjust

Y followed by dit/dah ratio
B followed by speed pot min WPM
T followed by speed pot max WPM
REV followed by firmware revision denoted by a single letter; A or B or C... etc.

You can abort this command at any time after the first parameter is sent by pressing the Command and PB4 pushbuttons together or holding either the left or right paddle.

R [pb] - Review a message without transmitting: After the **R** command is entered the K16-PS will respond with an **E**. Press the message button of the message you wish to play. The message will be sent in sidetone only. If you try to play an empty slot, the K16-PS will respond with **MT**. Embedded commands will be sent as is without expansion. In other words /S10TEST will be sent as: **DAH-DI-DI-DAH-DIT 10TEST**

S [nn] - Set Favorite Speed in WPM: One value is entered between 5 and 99. This speed is activated when the speed pot is turned fully counterclockwise. The speed pot will act normally above this setting.

The minimum WPM is 5 WPM, the maximum speed is 99 WPM.

T [nn] - Set PTT Tail Time: The K16-PS provides a transmitter PTT output that can be used to switch a transmitter or linear amplifier over to transmit mode in advance of actual CW keying. You have control over the time delay between when PTT is asserted and when CW keying will start, this is lead-in. You also have control over how long the transmitter will stay in transmit after keying has stopped this is tail delay. The tail delay is handled differently for CW sent by paddle and CW sent by message. Paddle delay is controlled by the Hang Time setting while message PTT delay is controlled by the Tail setting. The formula to calculate tail time is:

Tail Delay = Three Dit Times + (Tail Setting times 10 milliseconds)

Examples:

At 20 WPM, Tail set to 7, Tail Delay = $(3 \times 60) + (7 \times 10) = 250$ mSec
 At 40 WPM, Tail set to 7, Tail Delay = $(3 \times 30) + (7 \times 10) = 160$ mSec
 At 20 WPM, Tail set to 0, Tail Delay = $(3 \times 60) + (0 \times 10) = 180$ mSec
 At 15 WPM, Tail set to 55, Tail Delay = $(3 \times 80) + (55 \times 10) = 790$ mSec




Figure 22 – PTT Lead-in and Tail Example

In general we want a very short tail time when sending messages and we want PTT to stay asserted between letters while sending with a paddle set. That's the reason the delay is dictated by two mechanisms.

U - Toggle Autospace Mode Off and On: When autospace is enabled, the K16-PS will automatically insert proper inter-letter space between letters. When the **U** command is issued, the K16-PS will respond with an **A** for autospace enabled or an **N** for autospace disabled.

Here is how autospace works: If you pause for more than one dit time between a dit or dah K16-PS will interpret this as a letter-space and will not allow the next the next dit or dah to be started until the proper letter-space time has been met. The normal letter-space is 3 dits however this can be increased by using the **I** command. K16-PS has a paddle event memory so that you can enter dits, dahs, or squeeze both during the inter-letter space and K16-PS will send them as they were entered. With a little practice, autospace will help you to send near perfect Morse.

V [nn] - Keying Compensation: allows a fixed amount of time to be added to the length of all dits and dahs. QSK keying on modern transceivers can cause shortening of these elements which is especially noticeable at high speeds. The K16-PS allows the length of the elements to be increased uniformly to compensate for this. The adjustments can be made in one-millisecond steps. The maximum adjustment is 31 mSecs. Key compensation is very similar to Weighting in that any adjustment added to the dits and dahs is subtracted from the spacing so the resulting speed is not changed. The difference between weighting and

keying compensation is that compensation is independent of speed, so if 10 mSec of key compensation is selected, 10 mSec will be always be added regardless of speed. So be careful, using large values of keying compensation at high speeds may result in dits and dahs being run together with no spacing at all.




Figure 23 – Key Compensation

W [nn] - Key Weighting: can be adjusted in percentage from 25% to 75%. When set to 50 % the dit time is equal to the inter-element time, which is normal. Values less than 50 reduce weighting while values greater than 50 increase weighting. Note that weighting does not affect sending speed because any increase in keyed time is subtracted from spacing time. Reduction in weighting results in a thinner sound while increased weighting results in a heavier sound. Since weighting tracks speed, a given weighting will sound the same at all speeds.




Figure 24 – Key Weighting

X - Extended Keyer Commands

An additional set of commands are located in a sub menu. These commands are ones that are not entered very often so the additional paddle action is not a significant issue. Extended commands require two entries, an **X** followed by a sub command. Here is the procedure in detail:

Press and hold the command pushbutton and the K16-PS will respond with an **R**
 Enter an **X** and the K16-PS will respond with an **E** (command request)
 Enter desired Extended Command with additional parameters, if required.

A list of extended commands is provided in the next section.

Y [nn] - Set Dit/Dah Ratio: nn ranges from 33 to 66. Entering **Y 50** sets the standard 1:3 ratio. For example a value of **33** selects a dit/dah ratio of 1:2 while a value of **66** selects 1:4. The ratio formula is:

$$\text{Ratio of 1:N where } N = (nn * 3) / 50 \quad \text{example } nn = 40 \quad \text{give a ratio of } 1:((40*3)/50) = 1:2.4$$

Z - Change Sidetone Frequency: After this command is entered the sidetone oscillator will be keyed at a steady rate with transmit muted. Pressing the paddles will raise or lower the frequency. The range varies nearly continuously from 300 Hz at the low end to 2000Hz on the high end. It takes a while to sweep through the whole range. Pressing the command pushbutton will end this command and store the new sidetone frequency. Like all settings, use the Preserve Settings extended command to save the new sidetone setting in EEPROM.

Extended Command List

A – Pushbutton Input Diagnostic: is used to verify the correct operation of the switch network connected to K16-PS input pin 7. This design allows four switches and a potentiometer to share a single pin on the K16-PS. The state of the network generates a unique numeric value which is then handled appropriately, either as a pushbutton press or speed pot change.

After the Extended **A** command is issued, the numeric network state will be sent in Morse sidetone. For proper operation the input values must fall within the following ranges:

Command PB	0 to 11	PB 4	58 to 89
PB 2	12 to 31	Speed Pot	90 to 205 (approx)
PB 3	32 to 57		

The K16-PS will remain in this diagnostic state until power is cycled.

C - Toggle Contest Spacing: When contest spacing is enabled, word space is set to 6 dit times as opposed to the normal 7 dit times. An **A** is sent when CT space is enabled, an **N** is sent when it is turned off.

E[nn] - First Element Extension: Forces the first dit or dah of a transmission to be elongated to allow for receive to transmit delay. Enter a value between 0 and 99 mSecs for nn.

F - Toggle Fast Command Response Time: Normally the K16-PS will enter command mode when the command pushbutton is pressed for 2 seconds. This may be too long for some operators. When fast response is enabled, the delay time is reduced to 1.3 seconds.

M - Load Callsign: Use this command to load a stored callsign. It works just like a message entry and the destination is the currently enabled user slot. Each user slot has one unique callsign. Since the callsign is treated like any other message, embedded commands can be included if desired. The only way to play back a callsign is by embedding the **/M** command in a message.

N - Select Cut Number for number 9: When enabled, an N will be substituted for the number nine when sending a serial number. Command response: an **A** is sent when enabled, an **N** is sent when disabled.

P - Toggle PTT Mode: The user can choose whether to use PTT while keying. This is a toggle command and after it is entered, the K16-PS will respond with an **A** for PTT enabled, or **N** for PTT disabled. Please note that when PTT is enabled, the key output port is locked on port 1. If the toggle output port command is issued the K16-PS will respond with a **P** to indicate that PTT is enabled and swap is not allowed.

R [nn nn] - Set Speed Pot minimum and maximum: After the command is entered the K16-PS will prompt for two values, the minimum WPM and the maximum WPM. An error will be flagged if the minimum value entered is greater than the maximum, if the minimum value is less than 5 WPM. Maximum WPM allowed is 99.

S - Preserve Settings in EEPROM: will respond with a letter **R** to signify that settings were saved successfully.

T - Select Cut Number for Zero: When enabled, a T will be substituted for the number zero when sending a serial number. An **A** response means this cut is enabled, an **N** response means it is disabled.

U - Swap Users: The K16-PS provides two complete user configurations, each with a unique callsign. Both message banks are available to both users. This allows a universal set of messages to be created that will work with either user. For example a message like **CQ CQ CQ DE /M /M K** will send the selected user's callsign. In response to this command a single dit is echoed when user 1 is selected and two dits when user 2 is selected.

V - Voltage Readout: The K16-PS will measure the current supply voltage and send it in Morse sidetone. For example a voltage of 4.52 will be sent as **4r52** with the **r** indicating the decimal point.

X - Toggle paddle swap (Exchange dit/dah inputs): K16-PS will respond with a letter **A** to signify when paddle swap is enabled and an **N** when turned off.

PTT Functionality

K16-PS's PTT output is normally used to control an accessory device in addition to normal CW transmitter keying. In most cases this device is a linear amplifier but it could be an antenna relay or the PTT input of a transmitter. In all of these cases there are delay requirements that must be met to insure that the accessory device is switched on before transmission begins and is held on until transmission completes. This prevents damage to the accessory device due to hot switching. The K16-PS provides three independent PTT delays to meet this requirement; Lead In, Tail, and Hang Delay.

Lead-In delay initiates a keying event. PTT will be asserted first and then, after the Lead-In delay expires, the key output will be asserted. Lead-In can be set to a value from 0 to 990 milliseconds in 10 millisecond steps (0 to 99).

Tail Delay specifies the amount of time PTT will be released after Key is released. Like Lead-In delay, it is adjustable from zero to 990 milliseconds in 10 millisecond steps. Tail delay is the sum of two delays, Tail setting times 10 milliseconds plus three dit times.

Tail Delay = Three Dit Times + (Tail Setting *times* 10 milliseconds) *note: one dit time = (1200/WPM) mSec*

Examples:

At 20 WPM, Tail set to 7, Tail Delay = $(3 \times 60) + (7 \times 10) = 250$ mSec

At 40 WPM, Tail set to 7, Tail Delay = $(3 \times 30) + (7 \times 10) = 160$ mSec

At 20 WPM, Tail set to 0, Tail Delay = $(3 \times 60) + (0 \times 10) = 180$ mSec

At 15 WPM, Tail set to 55, Tail Delay = $(3 \times 80) + (55 \times 10) = 790$ mSec

In setting tail delay it is desirable to set the delay long enough to prevent hot switching. The K16-PS will hold PTT between letters for messages and then PTT will timeout after the last letter of a message is sent.

For paddle sending, most ops want PTT to be held just long enough to prevent drop out between letters. An issue arises in that Tail delay is not solely proportional to sending speed. This is problematic when someone sets a comfortable tail delay at a slow speed and then increases the speed to a much faster rate. At the faster rate, the tail delay will hold too long after keying stops. Alternatively, if a comfortable delay is set at a faster WPM rate, PTT will then drop out between letters at a slower speed. Since it is very time consuming to constantly adjust the tail delay with sending speed, a different delay method is used for paddle sending, namely Hang Time.

Hang Time is adjustable in four steps and is measured only in wordspace and dit times rather than fixed milliseconds. This means that the delay will track sending speed. In other words it will decrease automatically as sending speed increases and vice versa. The four settings for Hang Time are:

HangTime = 0: wait 1 wordspace + 1 dit before ending paddle insertion

HangTime = 1: wait 1 wordspace + 2 dits before ending paddle insertion

HangTime = 2: wait 1 wordspace + 4 dits before ending paddle insertion

HangTime = 3: wait 1 wordspace + 8 dits before ending paddle insertion

To sum up, Tail delay is set to provide just enough delay to prevent hot switching for machine sent CW while hang delay is designed to hold PTT between letters independent of sending speed. PTT will automatically be held between machine sent letters and words but will drop out quickly after a message has been sent as long as there is no trailing wordspace. When entering a message be sure to end the message with the di-dah-di-dah (AA) character to prevent the K16-PS from automatically appending a wordspace.

Shortcuts and Speed Ups

A goal for the K16-PS design was to streamline command entry, here are some notable improvements:

Fast Command responses – K16-PS uses **A** for positive responses instead of an **R** or **Y**

Cut Numbers on Command Entry – When entering numeric values use cut numbers to save time. For example when changing the command speed to 19 WPM, use **S U N** instead of **S 2 9**

These are the command cuts used in the K16-PS: T=0, A=1, U=2, V=3, 4=4, 5=5, 6=6, B=7, D=8, N=9

Single digit number entry – If you are entering a parameter that usually requires two digits but you only need to enter one, just enter the single digit and the K16-PS will figure out that there is only one. For example instead of entering **T 0 7** you can simply enter **T 7**.

K16-PS will respond with an **E** or **I** when swapping users, message banks, or output port. Think of it as a single dit for 1 and a double dit for 2. This is much faster than responding with a Morse 1 or 2.

Fast Message Entry – Just press the command button till you get an R then simply press the message button you want to load. To stop load mode, either press the command button or enter di-dah-di-dah.

Fast Tune Mode – Press and hold pushbutton 4 and then press the command button to start tune. Press the command button to end tune.

Fast Serial Number decrement – Press the command button and then press either paddle to decrement the serial number. The K16-PS echoes a single dit to signify that the command was accepted.

Fast Command Response – If you think the K16-PS takes too long to respond to the command button, enable fast command reply mode which halves the delay time. This is the extended command **F**.

Command Prompts – The K16-PS will respond to commands that require additional input with an **E**. The **E** stands for “Entry Required” and is fast and efficient. For example if you enter the Weight command **W**, the K16-PS will respond with an **E** to let you know it is waiting for the value.

Speed Potentiometer Configuration

Turning the speed control will change the speed and update the WPM rate with minimal lag. The entire sweep of the speed pot is called the speed pot range and it can be modified with the extended **R** command which sets the upper and lower speed limits. This allows you to tailor the speed control to an area that you prefer. The minimum acceptable value for speed bottom is 5 WPM. If you want to set an exact speed, the easiest way to do this is to turn the speed control fully counter clockwise and set the fixed speed to whatever you want using the **S** command. You can determine the current speed control setting with the **Q** (query) command. Turning the speed pot fully counterclockwise will select the fixed “favorite” speed.

Message Functionality

Messages are loaded by holding the command button until K16-PS responds with an **R**, and then pressing the message pushbutton of the memory slot you wish to enter. When K16-PS is ready to accept a new message it will respond with an **E**. If you wait too long, K16-PS will respond with a **?** and you will have to start over. Since only four pushbuttons are provided, messages 5 and 6 are accessed by pressing two pushbuttons in the following sequence after the **R** is echoed:

Press and hold either message button 2 or 3. (for message 5 or 6 respectively)
Press the command pushbutton.
Release both push buttons.

Message 5 and 6 can be played in a similar manner by first pressing and holding pushbutton 2 or 3, then pressing the command pushbutton, and finally releasing both. Don't forget that there are also two separate message banks each containing six slots bringing the total number of unique messages to 12.

After K16-PS responds with an **E**, a new message is entered directly on the paddles at a steady rate, making sure to leave proper space between letters. To insert a word space simply pause for longer than a word space and K16-PS will respond with an **E** to signify a word space insertion. You can force a wordspace insertion by entering di-di-dah-dah (**IM**). This allows you to put a wordspace at the beginning of a message or insert more than one wordspace in a row. A ½ letterspace pad character can be inserted by entering di-di-dah-dah-dit (**IG**).

If a mistake is made while entering a message, press and hold the command pushbutton and K16-PS will backspace through the letters that have been entered. When you reach the position you want, release the button and new letters can then be added starting at that position. If the message memory becomes full while entering a message, K16-PS will stop further loading, respond with an **F**, and then return K16-PS back to non-command mode. When a new message has been completely entered, press the command push-button, or enter di-dah-di-dah (**AA**), and K16-PS will respond with an **R** to signify that the message was accepted and stored. There are 232 letters in message memory that can be distributed in any way between 14 message slots. The length of the individual message slots is not fixed. This means, for example, you could have one message of 80 characters, one message with 5 characters, and a third with 10 characters and still have 141 locations left to split among the remaining three slots. Keep in mind that each word space occupies one memory location.

What if you want to insert one of the message controls (**IM**, **IG**, **AA**) into a message ? Simply precede them with a **/** (**DN**) and it will not be acted on as a control code.

Note that usually when you end a message, K16-PS will append a wordspace before you have a chance to press the command pushbutton. There are cases when you do not want a wordspace at the end, especially if you are using PTT to key an amplifier. This is because K16-PS will hold PTT during that added wordspace. The best way around this is to end a message with the di-dah-di-dah (**AA**) control code inserted immediately after the last letter in the message. This will terminate the message without a trailing word space.

If you are having problems loading messages into K16-PS, make sure you leave adequate space between letters and are not sending much faster or slower than current command speed. If, for example, you enter an **A** followed by a **T** and end up with a **W**, you are not allowing enough space between letters. It's a fine line though

because if you allow too much space K16-PS will interpret that as an intentional pause and insert a word space. Temporarily lowering the command speed (see command **C**) can help while you learn how the process works.

To play a message back, simply press the desired message button, release, and that message will be sent. If you press a pushbutton that does not have a message loaded, the K16-PS will respond with an **MT**, short for eMpTy. If you want to review the message without keying the transmitter, use the **R** (review) command. Note that review will ignore control codes and send them as entered. To abort a message, press the command and PB4 pushbuttons together or press and hold one of the paddles and K16-PS will stop transmission immediately.

Gap (Extra Space) Insertion

In messages, K16-PS interprets the **IG** prosign (di-di-dah-dah-dit) as a ½ dit delay time. The **IG** character can be included in a text string to add extra emphasis to similar sounding sequences. An example is W1OMO, sending it as W1**IG**O**IG**M**IG**O makes it easier to copy. To insert a **IG** prosign in a message without translating it to a gap, enter it as **/IG**.

Word Space Insertion

In messages, K16-PS interprets the **IM** prosign (di-di-dah-dah) as a 7 dit wordspace delay time. The **IM** character can be included to add a small amount of delay and is easier to use than a delay command. To insert an **IM** prosign in a message without translating it to a wordspace, enter it as **/IM**.

'Two Press' Message Button Functionality

As previously mentioned above, you can trigger message 5 and 6 directly with the following sequence:

- 1) Press and hold PB2 for message 5 or PB3 for message 6
- 2) Press the command PB (you now have two PBs pressed)
- 3) Now release both pushbuttons and selected message will play.

Quick Tune Command

If you use the sequence outlined above but start with PB4 instead, tune mode is turned on. This keys your transmitter until you press either paddle or PB1+PB4 at the same time. Use the **G** command to select either a 100% or 50% tune duty cycle.

Quick Serial Number Decrement

Sometimes during contest operation, a serial number has to be reissued. Since the serial number is automatically incremented when it's played, we need a way to decrement the serial number. This can be done one of two ways, using the **D** paddle command or by pressing and holding the CMD PB and then quickly pressing either paddle. In either case, after the serial number is decremented, K16-PS echoes a single dit.

There is a third way to decrement a serial number, that is with a **/D** command embedded in a message. A message can be built that pre-decrements the serial number before sending it. For example the following two messages can be created:

Message 1: 5NN /N QSL ?

Message 2: /D/N QSL ?

Message 1 is played as the initial exchange and if the serial number needs to be resent, message 2 would be used. The second message pre-decrements the serial number before sending it. Both of these messages leave the serial number incremented after it is sent. Here is a way to send the serial number twice in one message:

Message 3: /N/D /N

Embedded Message Command List

It is an easy procedure to embed commands in a message. The format is the fraction bar **DN** (D and N sent together as one letter) followed by the desired command letter. If you want to insert the DN prosign into a message but don't want it to be interpreted as a command simply enter DN twice.

Example: **K1EL/1** would be entered as **K1EL//1**

Embedded message command table

/Bnn	Set a beacon cycle time of nn seconds (nn=00 to 99). Put this at the beginning of a message to set the beacon period.
/Cn	Call message in slot n (1-6), return and resume current message.
/D	Decrement serial number.
/E	Toggle message banks
/Hn	Set HSCW speed. See table below for determining n.
/Inn	Increase letterspacing within a message, nn is a value from 0 to 31 percent times 2.
/Knn	Key transmitter for nn seconds. (nn=00 to 99)
/M	Play user callsign.
/N	Play Serial Number with auto post increment.
/On	Select key output port; 1 for port 1 or 2 for port 2.
/P	Pause and wait for paddle entry and then continue after one word space time. The pause is ended three ways 1) paddle entry 2) Press a msg PB (2-6) or 3) Press the cmd PB to cancel.
/Q	Set QRSS speed. See table below for determining n.
/Snn	Set a speed change within a message. (nn=WPM, 5 to 99)
/Un	Turn PTT on or off. PTT is turned on when n = 1 and off when n=0.
/V	Send the current voltage in Morse, useful for beacons.
/Wnn	Wait for nn seconds. (nn=00 to 99)
/Xn	Cancel speed override, for example cancel HSCW, QRSS, or /Snn speed.
/Yn	Force a relative speed change up. Add n to the current WPM. n=(0-9)
/Zn	Force a relative speed change down. Subtract n from the current WPM. n=(0-9)
/1	Jump to message 1
/2	Jump to message 2
/3	Jump to message 3
/4	Jump to message 4
/5	Jump to message 5
/6	Jump to message 6
AA	End message load immediately
IG	Insert ½ letterspace pad
IM	Insert wordspace pad
	(DI-DAH-DI-DAH)
	(DI-DI-DAH-DAH-DIT)
	(DI-DI-DAH-DAH)

Rate Table

n	HSCW Rate	QRSS Rate
0	1000 lpm (200 wpm)	3 sec dit
1	1500 lpm (300 wpm)	6 sec dit
2	2000 lpm (400 wpm)	10 sec dit
3	3000 lpm (600 wpm)	12 sec dit
4	4000 lpm (800 wpm)	30 sec dit
5	6000 lpm (1200 wpm)	60 sec dit

Embedded Command Examples

/B60BCON DE K1EL BEDFORD NH will send BCON DE K1EL BEDFORD NH every 60 seconds

UR RST IS /P QSL will pause to allow the user to enter the RST then resume automatically

/K05 /W10 VVV DE K1EL will key down for 5 secs, wait 10 secs, and then send VVV DE K1EL

CQ CQ CQ DE /M /M /M will send a 3x3 CQ using the user callsign

/H2CQ CQ DE K1EL K1EL K1EL/S15 DE K1EL will send 1st part at 1500 lpm and the 2nd at 15 WPM

CQ CQ CQ DE K1//10TMT//100 K will send message with 20% extra space in TMT. A more manageable way of doing this would be to load **K1//10TMT//100** in the callsign slot to get this spacing any time /M is used.

CQ CQ CQ DE /Z4K1EL K1EL K1EL/Y4 K send the callsigns 4 WPM slower then return to normal WPM.

QTH IS /E/C1/E NAME IS STEVE Will play the QTH from message bank 1 and then return for the name.

/Q2EL /1 will continuously send EL at QRSS10 speed (this message is in slot 1). Avoid inserting a space between the QRSS command and the start of text: /Q2 EL unless you want a long delay at start of message.

/B10K1EL BCON/W2/VVOLTS sends K1EL BCON, wait 2 secs, send XrXX VOLTS repeat every 10 secs

SOM/E/C3/E/U1/W5/U0/S50K1EL//1/XEOM Send SOM, swap to msg bank 2, call msg 3, swap back to msg bank 1, turn PTT on for 5 seconds, change speed to 50 WPM and send K1EL/1, cancel 50WPM send EOM.

Preserve Settings

K16-PS setting changes are not automatically copied into permanent storage. That means the settings will be lost if power is cycled. To save the settings permanently, use extended **S** command. Press and hold the command PB until the **R** and enter an **X** followed by a **S**. This will save current settings in nonvolatile memory so that all settings will be retained on power cycling. Note that messages are always saved directly into nonvolatile memory so the **S** command is not required to preserve messages.

Restore User Defaults (Warm Restart)

It's possible that a command could get entered by accident and put the K16-PS into an undesired state. An easy way to restore user default settings is to power off and on. Another way is to or press and hold the command pushbutton and keep holding after the **R** is sent. After an additional 5 seconds a **W** will be sent signifying that a warm reboot occurred which reloaded user defaults.

Restore Factory Defaults

If you want to restore the K16-PS to original "factory" settings hold the pushbutton down as you would for a warm restart and at the same time press and hold both paddles closed. Now instead of a **W** the K16-PS will send a **C** signifying a cold reboot which erases all settings and messages and then restores factory settings.

Factory Defaults are:

Fixed WPM: 15	Command WPM: 15	Sidetone: 800Hz	Weight: No adjustment
KeyComp: 0	Interchar Spacing: Normal	SampleAdjust: None	KeyMode: Iambic B
Sidetone: On	Autospace: Off	OutputMode: KEY/PTT	Serial Number: 0001
TX Mute: Off	User: 1	Message Bank: 1	Messages: All Erased
Speed Pot Min: 5	Speed Pot Max: 35	First Extension: 0	Farnsworth: Off
Dit/Dah Ratio: 1:3	Sidetone: On	Tune Duty Cycle: 100%	Extra Letterspace: None

Keyer Lock

A lock feature is provided to disable paddle input and message pushbuttons. This is useful when you want to pack up a battery powered keyer and insure that it stays off with batteries still connected. It is also handy to lock the keyer paddles to keep little hands from sending "messages". While the keyer is locked it is held in low power shutdown mode. To lock the keyer, press the command pushbutton, wait for the **R**, and then enter a period (di-dah-di-dah-di-dah). The K16-PS will respond with an **L** to let you know it is now in a locked state. To unlock the keyer, press and hold the both paddles closed for about 8 seconds and the K16-PS will wake up and send an **R**. This is a very reliable lock mechanism because once the paddles are removed there is no possible way to accidentally unlock the K16-PS.

K16-PS Command Cheatsheet

Immediate Command List

- | | |
|------------------------------------|---|
| A - Toggle sidetone on/off | N - Load 4 digit serial number |
| B - Easy Beacon | O - Swap keying output port |
| C - Set command speed in WPM | P - Start Practice Mode |
| D - Decrement serial number | Q - Query: Report current settings |
| E - Swap Message Banks | R - Review message without transmitting |
| F - Set Farnsworth Speed | S - Set Speed Pot Range |
| G - Toggle Tune Duty Cycle 50/100% | T - Set PTT Tail Delay |
| H - Set PTT Hang Delay | U - Toggle Autospacing on/off |
| I - Set Letter Spacing | V - Set Keying compensation in mSec |
| J - Set Paddle sensitivity | W - Set Key Weight |
| K - Select keyer mode | X - Enter Extended Command |
| L - Set PTT Lead In Delay | Y - Set Dit/Dah Ratio |
| M - Toggle Transmit Mute on/off | Z - Select sidetone frequency |

Extended Command List

- | | |
|-----------------------------------|------------------------------------|
| A - Analog Input Diagnostic | R - Set Speed Pot Min and Max WPM |
| C - Toggle Contest Spacing | S - Preserve Settings in EEPROM |
| E - First Element Extension | T - Toggle Number 0 Cut |
| F - Toggle Fast Cmd Response Time | U - Swap Users |
| M - Load Callsign | V - Voltage Readout |
| N - Toggle Number 9 Cut | X - Exchange dit/dah inputs (Swap) |
| P - Toggle PTT Mode | |

Embedded Message Command List

- | | |
|--|--|
| /Bnn - Set a beacon cycle time | /Un - Turn PTT On/Off (n=0 or 1) |
| /Cn - Call message (n=1-6) | /V - Send Voltage reading in Morse |
| /D - Decrement Serial Number | /Wnn - Wait for nn seconds (n=0-99) |
| /E - Swap message banks | /X - Cancel speed override |
| /Hn - Set HSCW Speed (n=0-5) | /Yn - Relative WPM change up (n=0-9) |
| /Inn - Set Alternate Letterspacing (n=0-31) | /Zn - Relative WPM change down (n=0-9) |
| /Knn - Key down for nn seconds (n=0-99) | /1 - Jump to message 1 |
| /M - Play user callsign | /2 - Jump to message 2 |
| /N - Play Serial Number | /3 - Jump to message 3 |
| /On - Select Key Output Port (n=0 or 1) | /4 - Jump to message 4 |
| /P - Pause and Wait for Paddle | /5 - Jump to message 5 |
| /Qn - Set QRSS Speed (n=0-5) | /6 - Jump to message 6 |
| /Snn - Set Sending speed in WPM (n=0-99) | <u>AA</u> - End message load |
| <u>IM</u> - Insert Wordspace (DI-DI-DAH-DAH) | <u>IG</u> - Insert Gap (DI-DI-DAH-DAH-DIT) |

Rate Table for H and Q Commands

n	HSCW Rate	QRSS Rate
0	1000 lpm (200 wpm)	3 sec dit
1	1500 lpm (300 wpm)	6 sec dit
2	2000 lpm (400 wpm)	10 sec dit
3	3000 lpm (600 wpm)	12 sec dit
4	4000 lpm (800 wpm)	30 sec dit
5	6000 lpm (1200 wpm)	60 sec dit

PS1 Tutorial

- 1) Power up: After power is applied, the K16-PS will output the letter R to let you know it's ready. Pressing the paddle keys will generate dits and dahs both in sidetone and keyed output.
- 2) Command Entry: A command cheatsheet can be found on page 29. There are three command types, immediate, extended, and embedded message. The first commands to look at are immediate commands. Press the command pushbutton (CMD PB) until the K16-PS answers with an **R**. Then without hesitation enter an immediate command letter on the paddles. Try the **Z** command which allows the sidetone frequency to be changed. The K16-PS will output a continuous tone and you can adjust the frequency by pressing the paddles. When you are finished press the command button to return to normal operation. If the K16-PS does not understand a command or you are too late to enter a command the K16-PS will respond with a question mark. Some commands require additional parameters a good example is setting the command speed. Press the CMD PB, wait for the **R**, and then enter **C**. The K16-PS will respond with an **E** telling you it's waiting for you to enter something. Enter a 1 followed by a 0. Try it again but this time use a **T** for the zero. This is a handy shortcut. You have changed the command entry speed to 10 WPM. If this is too slow, repeat the command with a more comfortable speed.
- 3) Change Keyer Mode: Enter the **K** command and the K16-PS will prompt you for desired keying mode. For example **A** for Iambic A, **B** for Iambic B, the full list is on page 19. The K16-PS will respond with an **A** to let you know it acknowledged the command. The sample adjust command **J** adjusts the paddle sensitivity to home in on the way you want the paddles to respond. By setting sample adjust to zero you can disable the dit and dah paddle memories. Weighting, Keying compensation, and letterspace are a few other ways to adjust the way Morse is generated.
- 4) Since we have more commands than letters in the alphabet, we added extended commands. They work just like immediate commands with the exception that you have to enter two letters. A useful extended command is the 'save settings' command **S**. Press the CMD PB to get an **R** and in response enter an **X** for extended command followed by an **S** for save. The K16-PS saves settings in nonvolatile memory so that when you power down and back up your preferred settings are preserved. Messages are automatically saved in memory when entered but settings have to be saved by the Save command. It works this way since most users may want to change settings temporarily but always want to go back to their favorite settings when they are done. It's easy to restore default settings, just press and hold the CMD PB until you get the **R** and keep holding until the K16-PS responds with a **W** for warm start. This means that settings have been restored. A nother interesting extended command is **V** which tells the K16-PS to report the current keyer supply voltage. It plays it in this form: **4r35** which in this case is 4.35 volts.
- 5) Now let's play with messages. Review the procedure for message loading on page 23. The K16-PS has two great features associated with message loading. The first is backspace, if you make a mistake while entering a message just hold the command button down and the K16-PS will back up letter by letter. The second is non-fixed message slot size, if you only use two bytes in slot one, only two bytes of message memory are used up, not an entire slot. We will load a message into slot 1. Press and hold the CMD PB until the **R** and then release and then press the CMD PB again. This tells the K16-PS you want to load a message into slot 1. You can load any other slot in the same manner. The K16-PS responds with an **E** to let you know it is ready to accept the message. On the paddles enter: **/S10SLOW /S25FAST**. (/ is the DN prosign DAH-DI-DI-DAH-DIT) This message has two embedded commands which will change the speed while the message is playing. **SLOW** at 10 WPM and **FAST** at 25 WPM. Note that after playing this message the operating speed will be returned to the initial starting speed.
- 6) It's easy to compose a beacon command: In msg slot 2 enter: **/B60/K05 BCON DE K1EL NH** This will key down for 5 seconds, send **BCON DE K1EL NH** and repeat every 60 seconds. To cancel a beacon simply press the CMD PB, K16-PS will stop the loop and respond with an X to let you know something was cancelled.
- 7) Next we will test out serial numbering. First enter a starting serial number using the **N** command. You need to enter all four digits including leading zeroes. You may want to select the way K16-PS will send 0s and 9s in a serial number. Use the two extended commands **N** and **T** for that (see page 23). Here is an example of a message that will play a serial number incorporating the **/P** pause command: **CQ DE K1EL/P UR NR /N QSL?/P**. This message will send CQ and then pause to let you listen for a reply. If no reply, hit the msg PB to repeat the CQ. If there was a reply, enter the station's callsign and the K16-PS will send the serial number and pause again. If the station needs a repeat of the callsign press 2 to play this message in slot 2: **UR NR /D/N QSL ?** Since the serial number is incremented after an **/N** command you need to pre-decrement it with **/D** to send the original number. The **/P** command is a three-way branch, 1st branch: paddle something to

- continue, 2nd branch: hit a msg button (other than CMD PB), 3rd branch: hit the CMD PB to cancel the message. Since MSG1 = CMD PB you can't use slot one as a 2nd branch choice.
- 8) The K16-PS supports two alternate sending rate modes. They are selected by putting embedded commands in the message. QRSS is extremely slow CW for VLF operation, while HSCW is extremely fast CW typically used for QSOs via meteor scatter. Here are examples of each:
QRSS: **/K10/ Q2EL/2** Keydown for 10 seconds followed by **EL** at QRSS6 rate, repeat.
HSCW: **/H3K1EL K1EL K1EL K1EL K1EL K1EL K1EL /1** Callsign is repeated at 3000 LPM
- 9) There are three K16-PS output modes.
Normal mode: Keying output on pin 2 and sidetone on pin 3.
AFSK mode: Pin 2 keys the transmitter, pin 3 provides a keyed tone to feed into a microphone.
External Oscillator mode: Used mainly for HSCW, the K16-PS keys an external crystal based tone oscillator.

INDEX

Paddle Stick Functional Block Diagram	3
Figure 1 – PaddleStick Block Diagram.....	3
Touch Paddle Configuration.....	3
PaddleStick Kit Introduction	4
PaddleStick Kit Assembly	4
Parts Inventory	4
PCB Assembly	4
Figure 2 - PaddleStick PC Board before assembly	4
Figure 3 – Cut paddle separator	5
Figure 4 – Free paddle piece and then trim off separator.	5
Figure 5 – Install socket, pin 1 to upper left, and solder in place.....	6
Figure 6 – Capacitor details	6
Figure 7 – Installs Resistors and Capacitors.....	7
Figure 8 – Install Transistors and Voltage Regulator	7
Figure 9 – Install Speaker and Jumper	8
Figure 10 – Trim foam panel to fit within paddle edges.....	9
Figure 11 – Attach foam panel to free paddle, peel off backing.	9
Figure 12 – Join free paddle to main paddle board.....	9
Figure 11 – Detail view of free paddle in place.	10
Figure 12 – Completed assembly, power leads attached.	10
Figure 13 – Completed assembly, side view.....	11
Test Procedure	11
How to connect your PaddleStick	12
Figure 14 - PaddleStick Connection Diagram	12
Keyer Mounting.....	12
Figure 15 – Base mount illustration.....	13
Figure 16 – Front panel mount illustration.....	13
Figure 17 – Picture of brackets installed	13
Keying Considerations	14
Input Considerations	14
Command and Message Push-buttons.....	14
Speed Pot	14
PaddleStick Kit Schematics	15
Figure 18 – PaddleStick Schematic	15
PaddleStick PCB Images	16
Figure 19 – PaddleStick Silk Screen PCB Layer.....	16
Operating the PS1/K16-PS Keyer IC	17
Command Mode	17
K16-PS Command List	17
Figure 22 – PTT Lead-in and Tail Example.....	20

Figure 23 – Key Compensation.....	21
Figure 24 – Key Weighting.....	21
Extended Command List.....	21
PTT Functionality	22
Shortcuts and Speed Ups	23
Speed Potentiometer Configuration	24
Message Functionality	24
Gap (Extra Space) Insertion.....	25
Word Space Insertion	25
'Two Press' Message Button Functionality	25
Quick Tune Command	25
Quick Serial Number Decrement	25
Embedded Message Command List	26
Embedded Command Examples	26
Preserve Settings.....	27
Restore User Defaults (Warm Restart)	27
Restore Factory Defaults	27
Keyer Lock.....	27
K16-PS Command Cheatsheet.....	28
Immediate Command List	28
Extended Command List.....	28
Embedded Message Command List	28
PS1 Tutorial	29
INDEX.....	31
Revision History	32

The PS1 keyer is fully guaranteed; if you are not satisfied please return the PS1 for a full refund.
Questions will be handled by snail-mail or e-mail via these addresses:

Steven T. Elliott K1EL
43 Meadowcrest Drive
Bedford, NH 03110 USA

or e-mail: k1el.kitsinfo@gmail.com

Watch the K1EL Website for latest updates and new product offerings: <http://www.k1el.com>

Revision History

Chip Rev -01 Original Release

Changed C1 to .47uF

Now shipping kit with BS170s for Q1 and Q2. These parts do not need to be installed in reverse.